

Caricabatterie Automatici / Automatic Battery Chargers

MEM 70 - 110 Automatic

electromem
Battery Chargers & Starters

Caricabatterie con dispositivo elettronico per il controllo della tensione di carica, costruiti in tre modelli specifici per essere utilizzati su gran parte dei mezzi in circolazione (moto, auto, furgoni, ecc.). Adatti a tutti i tipi di batterie al piombo: ad elettrolita libero, trattenuto, gel ed ermetiche. Possono rimanere collegati permanentemente senza il rischio di danneggiare le batterie. Lo speciale circuito mantiene stabilizzata la carica e provvede automaticamente al ripristino in caso di necessità.

Battery chargers with electronic device for charge voltage checking, manufactured in three specific models to be used in mostly means of transport (bikes, cars, vans, and so on). They are suitable for all types of lead batteries: free and held electrolyte, gel and hermetic batteries. They always can stay connected without damaging the batteries. The special circuit keeps stabilized the charge and in case of using it provides the regeneration automatically.



AUTOMATIC

**EASY
to USE**



- Carica automatica a tre fasi con fase di mantenimento
- Led di segnalazione: alimentazione, carica in corso, batteria carica, inversione di polarità
- Selettore della capacità della batteria e del tipo di batteria GEL-WET (Mem110);
- Attacchi alla batteria con pinze (in dotazione);
- Protezione termica a ripristino automatico;
- Protezione contro le inversioni di polarità e corto-circuiti;

- Three step of automatic charge with maintenance fase
- Signalling leds: power supplying, charging in progress, charged battery, reverse polarity
- Battery capacity selector and type of battery selector GEL-WET (Mem110);
- Battery connection with clamps (equipped);
- Thermic protection in automatic resetting;
- Protection against polarity inversions and short-circuits.



Caricabatterie automatico a controllo elettronico.
Automatic battery charger with electronic control.

Pb/ Normal-Wet-Dry-Gel-Agm-Mf



Manico in gomma per una presa più sicura.
Rubber handle for a safe grip.



Tasche per l'alloggiamento del cavo di alimentazione e dei cavi batteria.
Pockets to hold power cable and battery cables.

Model	Mains Voltage 50/60 Hz 1 Ph Volt	Power Watt	Output Voltage Volt	Charge Current Eff. Amp	Charge Current Arith. Amp (d.c.)	Nominal Capacity to refer to Ah min	Size mm	Weight kg	Cod. N
Mem 70 Automatic	230	80	12	6	4	20-70	200 x 75 x 190	2,1	16020
Mem 110 Automatic Gel-Wet	230	110	12	8	5,5	20-110	255 x 95 x 235	2,7	16030